Series 31 Shrink Boot Adapters



for MIL-DTL-38999 Series III and IV Connectors

310H*057 Shrink Boot Adapter, Pre-installed Boot, EMI Band Adapter, Composite



- Pre-installed boot
- 50% faster installation
- **Environmental**
- Adhesive lined boot
- Corrosion-proof composite material
- **EMI** banding adapter

Adapter Code H



This accessory fits these connectors: MIL-DTL-38999 Series III and Series IV

FIG. 1: NFS PLATING



Banding Adapter with selective NFS plating finish

BAND

Terminate cable braid to adapter with banding strap, Glenair's Band-Master ATS® banding system provides quick, easy, cost-effective and highly reliable termination of braid shield. Stainless steel.






Micro Band

Hand Tool 601-101

Pre-Coiled Band P/N	Length	Max Dia.				
601-061	8.13 (206)	.88 (22.4)				
601-065	14.25 (362)	1.80 (45.7)				

Fast installation, shielded, environmental, self-locking. 310H*057 "piggyback" shrink boot adapter fits MIL-DTL-38999 Series III and IV connectors. Use with jacketed, shielded cable. Terminate cable overbraid to EMI banding adapter with optional stainless steel microband. Piggyback boots reduce boot installation time by 50% and eliminate misalignment problems. Anti-decoupling mechanism provides audible detented coupling and prevents backoff under high vibration. Three boot materials: Type 1 high performance elastomer, Type 2 zero halogen or Type 3 flexible polyolefin Coupling nut and adapter body are PEI thermoplastic. EMI adapter is brass. Silicone O-ring, polyamide hot melt adhesive.




	Type 1 High Performance	Type 2 Zero Halogen	Type 3 General Purpose
Material	Semi-Rigid Elastomer	Semi-Rigid Polyolefin	Flexible Polyolefin
Resistance to Fuels, Oils	Excellent	Very Good	Good
Adhesive Type	W1 Hot Melt	W1 Hot Melt	W2 Hot Melt
Continuous Operating Temp.	-55 to +125 °C	-55 to +125 °C	-55 to +70 °C
Low Smoke/Zero Halogen	No	Yes	No
SAE Material Type	AS5258 Type H	AS5258 Type G	AS81765/1 Type 1

Series 31 Shrink Boot Adapters



for MIL-DTL-38999 Series III and IV Connectors


310H*057 Shrink Boot Adapter, Pre-installed Boot, EMI Band Adapter, Composite





After Shrinking

Shell		ø Ma	_	•	C Flats	ø M		ø Ma	
Size	A Thread	in	mm	in	mm	in	mm	in	mm
9 (A)	M12X1.0-6H	.86	21.8	.750	19.1	.250	6.4	.197	5.0
11 (B)	M15X1.0-6H	.98	24.9	.875	22.2	.355	9.0	.197	5.0
13 (C)	M18X1.0-6H	1.16	29.5	1.000	25.4	.491	12.5	.236	6.0
15 (D)	M22X1.0-6H	1.28	32.5	1.125	28.6	.565	14.4	.236	6.0
17 (E)	M25X1.0-6H	1.41	35.8	1.250	31.8	.690	17.5	.276	7.0
19 (F)	M28X1.0-6H	1.52	38.6	1.375	34.9	.769	19.5	.335	8.5
21 (G)	M31X1.0-6H	1.64	41.7	1.500	38.1	.894	22.7	.394	10.0
23 (H)	M34X1.0-6H	1.77	45.0	1.625	41.3	1.019	25.9	.394	10.0
25 (J)	M37X1.0-6H	1.89	48.0	1.750	44.5	1.134	28.8	.591	15.0

45°







90°